



LED T5 Ballast Compatibility Chart

Brand*	Model No.	Start Method	Lamp Connection	# Lamps 120Vac	# Lamps 277Vac	# Lamps 120Vac	# Lamps 277Vac
EIKQ	PM-4X54T5 UNV PS	PS	Series	3	3	4	4
Fulham	RHA-UNV-254-LT5	PS	Series	1	1	2	2
Fulham	RHA-UNV-454-LT5	PS	Series	3	3	4	4
General Electric	GE254MVPS90-A	PS	Parallel	1	1	2	2
General Electric	GE454MVPS90-E-S	PS	Parallel	3	3	4	4
General Electric	GE454MVPS90-F	PS	Parallel	3	3	4	4
HOWARD INDUSTRIES	EP2/54HO/PRS/MV/W/MC	PRS	Series	1	1	2	2
KEYSTONE	KTEB-254HO-UV-PS-SL	PS	Series	1		2	2
Keystone	KTEB-254HO-UV-TP-PS	PS	Series	1	1	2	2
KEYSTONE	KTEB-454HO-UV-PS	PS	Series	3	3	4	4
LumaPro	4KGE7A EB-454PRS-U	PS	Series	3	3	4	4
Maxlite	SKEU542HOP	PS	Parallel	1	1	2	2
OSRAM	QTP 4x54T5HO/UNV PSN HT W	PRS	Series			4	4
OSRAM SYLVANIA	QHE 2x54T5HO/UNV PSN	PRS	Series	1	1	2	2
OSRAM SYLVANIA	QTP 4x54T5HO/UNV PSN HT W	PRS	Series			4	4
Philips-Advance	HCN-2S54-90C-WL	PS	Series				
Philips-Advance	ICN-2S54-90C-N	PS	Series	1	1	2	2
Philips-Advance	ICN-2S54-90C-T	PS	Series	1	1	2	2
Philips-Advance	ICN-2S54-T	PS	Series	1	1	2	2
Philips-Advance	ICN-4S54-90C-2LS-G	PS	Series	3	3	4	4
Plusrite	BAF254PS/MV	PS	Series	1	1	2	2
Plusrite	BAF454PS/MV	PS	Series	3	3	4	4
TCP	E2P54PRSUNVE	PS	Parallel	1	1	2	2
Ultrasave	ER254120MHT-W	PS	Series			2	2
Universal Lighting Technologies	B254PUNVHB-D	PS	Series	1	1	2	2
Universal Lighting Technologies	B454PUNV-E	PRS	Series	3	3	4	4
Universal Lighting Technologies	B454PUNVHB-E	PRS	Series	3	3	4	4

Applies to the following Satco products:

S9710, S9711 & S9712

25 Watt T5

This list is current as of Jan. 2016. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners

Copyright© 2015

Satco Products, Inc.

All Rights Reserved.

Rev. Jan. 29 2016

Distribution Centers:

New York, Florida,

Texas, Washington,

California, Puerto Rico

National Toll-Free:

800-43-SATCO

(800-437-2826)

www.satco.com

110 Heartland Blvd.

Brentwood, NY 11717

PH 631-243-2022

FX 631-243-2027